

## Programming a Light

### **Note:**

Confirm the Light has been securely placed on the line and has gone through the boot cycle. Programming a Light will require both hands.

### **Understanding Light Numbers:**

After Starting the Light Picking software, you should notice 2 buttons that can be used to display assigned Light Numbers.

**Show Light Address** – Displays the current Light Number assigned.

**Show Gateway Address** – Displays the current Gateway and Light Number assigned. The first digit before the dash is automatically assigned by the Gateway the light is connected to and cannot be programmed.

### **Programming a Light**

1. Using your left hand, press and hold the 2 left buttons.



2. Take your right hand, tap the big button on the right and then let go of all buttons.



3. If done correctly the light will be in programming mode and display its current number.



4. Once in programming mode, the 2 left buttons will increase and decrease the value of the current number. The big button will move the cursor right one space.



5. After setting the desired number, tap the big button until the Light turns off to finalize the programming.

